EMINENT

DATASHEET: EM7550

HDMI™ 2-to-1 SwitchBox

HIGH DEFINITON VIDEO UP TO 1080p | DIGITAL AUDIO | LED INDICATORS | HDCP PASS-THROUGH

TECHNICAL SPECIFICATIONS:

Input Video Signal:	0.5~1.0 Volts p-p
Input DDC Signal:	5 Volts p-p (TTL)
HDMI™ Inputs:	2
HDMI™ Outputs:	1
HDCP:	HDCP 1.0/1.1/1.2
HDMI™ :	1.3b
Display Selection:	Push Button
Video amplifier bandwith:	2.5Gbps/250Mhz
Switching:	Intelligent and mechanical
Dimensions:	5.7cm x 4.6cm x 1.3cm

SYSTEM REQUIREMENTS:

EAN CODE: 8716065233049

Easily switch between 2 HDMI sources

With the Eminent EM7550 HDMI™ 2-to-1 SwitchBox easily allows you to connect various HDMI sources to a HDTV/Monitor. By pressing one button you can easily switch between your audio/video players. A LED indicates which port is selected. With the Eminent EM7550 HDMI™ 2-to-1 SwitchBox there is no need for changing cables anymore. The Eminent HDMI™ 2-to-1 SwitchBox is compatible with all HDMI devices like your Settop Box, your HDMI DVD Player, your Game Console, your Desktop Computer or your Notebook. The EMINENT EM7550 Supports high resolution input:PC: VGA, SVGA, XGA, SXGA and UXGA (1600x1200) & higher. HDTV: 480i, 576i, 480p, 576p, 720p, 1080i and 1080p.

- HDMI™ 2-to-1 SwitchBox
- Share 2 HDMI sources with a single HDTV/Monitor
- Simple and reliable
- Easy to install and simple to use
- Simply switch by the press of a button
- Ideal for home theater integration, presentation, conference rooms and retail stores
- Solid plastic housing, LED indicators
- No power supply needed
- Easy installation
- 5-Year warranty
- Accessible helpdesk
- Multilingual user manual

©2009 EMINENT